

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922) 49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Ижевск (3412)26-03-58
Иваново (4932)77-34-06
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижегород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Саранск (8342)22-96-24
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сыктывкар (8212)25-95-17
Сургут (3462)77-98-35
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольяти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Улан-Удэ (3012)59-97-51
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-61
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://peakii.nt-rt.ru> || pae@nt-rt.ru

Многопараметрический измеритель Р-520



Main Features

- Large LCD screen with controllable white backlight.
- Humanized designs like rack and skid proof shell make it more convenient for users.
- Double-parameter and equipped with pH electrode and conductivity electrode, can recognize electrode automatically.
- Built-in microprocessor chip with functions of auto calibration, auto temperature compensation, data storage, function setup, self-diagnosis, auto power off, low voltage display.
- Auto recognition of standard pH buffers and there are three series of standard buffers for option: USA, NIST and China.
- Able to set pH measurement modes of high purity water and pure water with ammonia.
- Auto recognition of 8 standard conductivity buffers and there are two series of standard buffers for option: USA series, China series.
- Adopt advanced conductivity measurement technology, one point calibration of conductivity electrode can meet the measuring accuracy requirements for test $0.5\mu\text{S/cm} \sim 200\text{mS/cm}$.
- Able to switch between conductivity, TDS, salinity and resistivity multinomial calculation for TDS and salinity to ensure the conversion precision of the full scale.
- Conductivity mode has the function of non-linear temperature compensation for high purity water.
- IP57 and equipped with calibration solution. There is optional carrying case.

Specifications

PH	Measuring range	(-2.00 ~ 19.99) pH
	Resolution	0.1/0.01 pH
	Accuracy	±0.02 pH
	Input current	≤2×10 ⁻¹² A
	Input impedance	≥1×10 ¹² Ω
	Stability	±0.01 pH/3h
	Temp compensation	(0 ~ 100)°C (automatic)
mV	Measuring range	-1999mV ~ 0 ~ 1999mV
	Resolution	1 mV
	Accuracy	±0.1% FS
Conductivity	Measuring range	Conductivity : (0.00 ~ 19.99) μS/cm (20.0 ~ 199.9)μS/cm (200~1999)μS/cm (2.00 ~ 19.99)mS/cm (20.0 ~ 199.9)mS/cm TDS: (0 ~ 100) g/L Salinity: (0 ~ 100) ppt Resistivity: (0 ~ 100) MΩ·cm
	Resolution	0.01/0.1/1μS/cm, 0.01/0.1 mS/cm
	Accuracy	Electrode: ±1.0% FS, Instrument:±1.5%FS
	Temp compensation	(0 ~ 100)°C (automatic)
	Electrode constants	0.1/1/10 cm ⁻¹
	Reference temperature	25°C, 20°C, 18°C
	Others	Data storage
	Storage contents	Series number, measuring value measuring unit and temperature
	Power	Two AA batteries(1.5V×2)
	Dimensions & Weight	160×90×30mm/360g (instrument) 480×300×60mm/1KG (with packing)
Working Condition	Ambient temperature	(5 ~ 35)°C
	Ambient humidity	≤85%
	IP grade	IP57

Standard Configuration

1. P-520 pH/Conductivity meter 1 unit
2. pH electrode 1 pc
3. Conductivity electrode 1 pc
4. Temperature electrode 1 pc
5. pH buffer (pH4.00, pH6.86, pH9.18/50ml) 1 set
6. Backup AA battery 2 pcs
7. Operation manual 1 copy

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922) 49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Ижевск (3412)26-03-58
Иваново (4932)77-34-06
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Россия (495)268-04-70

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Саранск (8342)22-96-24
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сыктывкар (8212)25-95-17
Сургут (3462)77-98-35
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Казахстан (772)734-952-31

Тольяти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Улан-Удэ (3012)59-97-51
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93